

# KR Electronics

## General Description

KR 2786-5 is a 43.875 MHz differential bandpass filter. The filter has a typical 3 dB bandwidth of 2.7 MHz and is designed for a balanced source and load impedance of 100  $\Omega$ . Other passband frequencies are available. Please consult the factory.



## Features

- 43.875 MHz Center Frequency
- DIP Package
- 100  $\Omega$  Differential Source and Load

## Typical Performance

**Passband Amplitude**  
(1 dB/div)

**Overall Response**  
(10 dB/div)



KR Electronics, Inc.  
91 Avenel Street  
Avenel, NJ 07001


Web [www.krfilters.com](http://www.krfilters.com)  
Email [sales@krfilters.com](mailto:sales@krfilters.com)  
Phone (732) 636-1900  
Fax (732) 636-1982

# KR Electronics 2786-5

## Specifications

Parameter	Specification
Filter type	Bandpass
Center Frequency	43.875 MHz
Insertion Loss	3 dB typical
3 dB Bandwidth	2.7 MHz Typical
40 dB Bandwidth	14 MHz Typical
Source and Load	100 Ω Differential

## Physical Dimensions



**NOTES:**

1. FILTER IS BI-DIRECTIONAL
2. ALL PINS ARE 0.030" DIA
3. DIMENSIONS ARE IN INCHES

- Pin 1—IN  
Pin 8—IN  
Pin 4—OUT  
Pin 5—OUT

Connect all remaining pins to GND (also connected to Case)