


# Lowpass Filter

KR Model  
2289-65


## Passband Amplitude & Group Delay



100 KHz

65 MHz

## Overall Amplitude




100 KHz

175 MHz

## Specifications

<b>KR Part Number</b>	<b>2289-65</b>
<b>Filter Type</b>	Lowpass
<b>Insertion Loss</b>	< 1 dB
<b>End of Passband &lt; 4 dB</b>	65 MHz
<b>Start of Stopband &gt;45 dB</b>	75.08 MHz
<b>Source and Load Impedance</b>	50 Ω

## Outline Drawing



PIN 1 - INPUT  
 PIN 9 - OUTPUT  
 PIN 2 THRU 8 - GROUND  
 UNIT IS UNENCAPSULATED - PARTS ARE EXPOSED

**KR Electronics**  
 www.krfilters.com  
 91 Avenel Street  
 Avenel, NJ 07001  
 732-636-1900